

**M.Sc. 4th Semester Examination, 2025****ELECTRONICS***( RF and Microwave System )***PAPER – ELC-403A***Full Marks : 50**Time : 2 hours*

Answer any **four** questions each from Group-A and Group-B and **two** questions from Group-C

*The figures in the right hand margin indicate marks*

*Candidates are required to give their answers in their own words as far as practicable*

**GROUP—A**

Answer any **four** questions :  $2 \times 4$

1. The S, matrix of a network is given by

$$[S] = \begin{bmatrix} 0.3 & 0.4 \angle 30^\circ \\ 0.4 \angle -30^\circ & 0 \end{bmatrix}$$

( Turn Over )

( 2 )

Determine whether the network is matched, reciprocal and lossless ?

2. Design a  $50\Omega$  branch line coupler at frequency 2.4 GHz.
3. Write the frequency range represented by C band and W band.
4. Determine the Q-factor of an air filled square resonator having dimension 2cm.
5. Name the device that is used to protect a microwave source from the entry of the reflected wave.
6. What is the mode jumping of magnetron and how it can be overcome ?

**GROUP—B**

Answer any four questions :  $4 \times 4$

7. A lossless T junction has impedance  $50\Omega$ . Find the output characteristic impedance so that the energy divides in 2 : 1 ratio. 4
8. A continuous wave rader operating at a frequency of 150 MHz. is used to detect a moving target whose relative velocity is 5 m/s. Determine the doppler frequency. 4
9. How velocity modulation is achieved and what is it's importance ? 4
10. Derive Radar range equation. 4
11. How diode with negative resistance can be used as a switch ? 4
12. Show that path loss is inversely proportional to wavelength. Calculate is path loss of Geo-stationary satellite in X-band of operation. 4

**GROUP - C**

**Answer any two questions :  $8 \times 2$**

**13. Describe how negative resistance is obtained in Zener diode ? Draw the equivalent circuit and find its input impedance.  $3 + 2 + 3$**

**14. Show that a three port network cannot be designed holding properties matched, reciprocal and lossless simultaneously. Hence derive the normalized S-parameter for right hand circulator and left hand circulator.  $4 + 4$**

**15. A 4 port microwave network has the following properties :  $8$**

- It show no reflections when all the ports are matched.
- When some power is applied at port 1, 40% of the input power comes out at port 2 and 40% comes out at port 3.

( 5 )

Also, the signals in port 2 and port 3 are in phase.

- When power is applied at port 4, 40% of the input power goes to port 2 and the signal in port 3 is 180 degrees out of phase with that in port 2.
- The network is symmetrical

Determine the scattering matrix of the network.

16. A radar is operating at 4 GHz and radiates 12kW peak power. Determine the physical area of the radar antenna if the target of  $10\text{m}^2$  RCS located at 50km away from the radar intercepts 10 mW power. The antenna has an aperture efficiency of 80%. 8

**[ Internal Assessment – 10 Marks ]**

---

# THE HISTORY OF THE UNITED STATES

FROM THE EARLIEST SETTLEMENTS TO THE PRESENT

BY JAMES M. SMITH

NEW YORK: THE CENTURY CO., 1900

Copyright, 1900, by James M. Smith

Printed in the United States of America

By the Century Company, New York

Published by the Century Company, New York

100 N. W. CORNER OF 4TH ST. N. Y. C.

SOLE AGENTS: THE CENTURY CO., NEW YORK

100 N. W. CORNER OF 4TH ST. N. Y. C.

SOLE AGENTS: THE CENTURY CO., NEW YORK

100 N. W. CORNER OF 4TH ST. N. Y. C.

SOLE AGENTS: THE CENTURY CO., NEW YORK

100 N. W. CORNER OF 4TH ST. N. Y. C.

SOLE AGENTS: THE CENTURY CO., NEW YORK

100 N. W. CORNER OF 4TH ST. N. Y. C.

SOLE AGENTS: THE CENTURY CO., NEW YORK

100 N. W. CORNER OF 4TH ST. N. Y. C.

SOLE AGENTS: THE CENTURY CO., NEW YORK

100 N. W. CORNER OF 4TH ST. N. Y. C.